

WiFi 接続後、ブラウザで <http://192.168.1.1/> へアクセスすると以下の画面が表示

The screenshot displays the Alcatel Onetouch web interface. At the top, the logo "ALCATEL onetouch." is on the left, and "HSDPA NTT DOCOMO" with signal strength, roaming, and Wi-Fi icons is on the right. Below the header is a navigation bar with "Quick Setup", "Connection", "SMS", and "Settings" tabs, along with "Help" and "Logout" buttons. The main content is split into two columns. The left column, titled "Login", contains a "Language" dropdown menu set to "English", a "Password" input field (highlighted with a red box), and a "Login" button. Below the button, red text reads "↑ admin と入れ ログイン ボタンを押す". The right column, titled "Connection Status", shows three sections: "Connection Status" (Connected, 7.13 MB usage, 01 minute duration), "WAN Status" (NTT DOCOMO network, HSDPA type, No roaming, IP 100.115.175.40), and "WLAN Status" (On, SSID Yoigo-W800Z-68DBE6, Security WPA2 PSK).

ALCATEL onetouch. HSDPA NTT DOCOMO

Quick Setup Connection SMS Settings Help Logout

Login

Language
English

Password

Login

↑ admin と入れ ログイン ボタンを押す

Connection Status

Connection Status

Connection Status: Connected
Usage: 7.13 MB
Duration: 0 day 0 hour 01 minute

WAN Status

Network Name: NTT DOCOMO
Network Type: HSDPA
Roaming: No
IP Address: 100.115.175.40

WLAN Status

WLAN Status: On
SSID: Yoigo-W800Z-68DBE6
Security: WPA2 PSK

Quick Setup

Connection

SMS

Settings

Help

Logout

Connection Status

Connection Status

⊙ Connection Status

Profile Management

←ここをクリック

Network

Active Profile:

Disconnect

PIN Code Management

Usage:

Connection Mode 7.17 MB

Duration:

0 day 0 hour 02 minutes

[Usage History](#)

⊙ WAN Status

Network Name: NTT DOCOMO
Network Type: HSDPA
Roaming: No
IP Address: 100.115.175.40

⊙ WLAN Status

WLAN Status: On
SSID: Yoigo-W800Z-68DBE6
Security: WPA2 PSK
User(s): 1/10

Turn Off

[Connected Device\(s\)](#)

Quick Setup

Connection

SMS

Settings

Help

Logout

Profile Management

2. APN 情報を入力

Profile Management:	<input type="text" value="umobile (D)"/>
*Profile Name:	<input type="text"/>
*Dial Number:	<input type="text"/>
APN:	<input type="text"/>
User name:	<input type="text"/>
Password:	<input type="text"/>
Protocol:	<input type="text" value="None"/>

Note: The max number of the profile you can create is 15.

1. New を押す

New

Edit

Save

Delete

Set Default

Quick Setup

Connection

SMS

Settings

Help

Logout

Profile Management

Profile Management: umobile (D)

*Profile Name: umobile

*Dial Number: *99***1#

APN: umobile.jp

User name: umobile@umobile.jp

Password:

Protocol: CHAP

umobile

SIM カードの設定例

password は、umobile

Note: The max number of the profile you can create is 15.

New

Edit

Save

Delete

Set Default

↑ フォームに SIM の情報記入後、Save を押す

Quick Setup

Connection

SMS

Settings

Help

Logout

Profile Management

Profile Management:

- docomo1
- bmobile
- docomo2
- ocn
- ✓ umobile (D)

*Profile Name:

umobile

*Dial Number:

*99***1#

APN:

umobile.jp

User name:

umobile@umobile.jp

Password:

.....

Protocol:

CHAP

←umobile が選択されてる
か確認。

(されていない場合は
umobile を選択し Set Default を押す)

Note: The max number of the profile you can create is 15.

New

Edit

Save

Delete

Set Default

Logout し、Connection Status が Connected になっていれば設定完了です。

ALCATEL onetouch. HSDPA NTT DOCOMO

Quick Setup Connection SMS Settings Help Logout

Login

Language
English

Password

Login

Connection Status

Connection Status: **Connected**

Usage: 9.97 MB

Duration: 0 day 0 hour 18 minutes

WAN Status

Network Name: NTT DOCOMO

Network Type: HSDPA

Roaming: No

IP Address: 100.115.175.40

WLAN Status

WLAN Status: On

SSID: Yoigo-W800Z-68DBE6